

Spec Mini-Press 9900 Series

This new knurled filter is designed to be pressed into place and create a reliable mechanical bond. This feature makes it an excellent selection for applications where soldering is undesirable. Suitable plating is available that allows gold bonding to the terminals.

Applications

These filters are ideal for microwave and RF applications such as attenuators, synthesizers, and oscillators. They perform well in high impedance circuits where large capacitance values are not practical.

Installation

- .136" to .137" (3.45-3.48mm) diameter hole
- Hole must be free of all insulating materials.
- Installation tool must have a hole of sufficient depth and diameter to accept the terminal of the filter.
- Installation force must be applied gradually and smoothly until the flange of the filter is seated against the receiving part (request installation instructions).

Mechanical Specifications

 Installation
 Press-in

 Plating
 Gold


Seal Glass sealed on one end, resin sealed on the other end

Termination Options Plating suitable for gold


bonding

Operating Temperature -55°C to +125°C

Circuit Schematic









Part Number: SCI-9925-200

		Rated Voltage			Minimum Insertion Loss (dB)						
		125°C	- 1		1	10	30	100	300	1	10
Part Number	Figure	DC	Amp	Сар	MHz	MHz	MHz	MHz	MHz	GHz	GHz
† SCI-9925-153	1	50	5	0.015 µF +100%/-0%	7	25	30	40	40	60	60
†SCI-9925-303	1	50	5	0.030 μF +100%/-0%	10	30	35	45	50	55	55
†SCI-9925-502	1	100	5	5000 pF +100%/-0%	_	15	20	30	35	45	55
† SCI-9925-000	1	200	5	10 pF max.	_	—	—	_	—	10	10
† SCI-9925-101	1	200	5	100 pF +100%/-0%	_	_	_	3	10	20	28
† SCI-9925-501	1	200	5	500 pF +100%/-0%	_	_	_	15	22	35	40
† SCI-9925-122	1	200	5	1200 pF +100%/-0%	_	5	10	20	28	35	45

⁺ Also available through Spectrum Control's authorized distributors.